# BL Casambi Dimmer 4CH PWM

**BL Casambi Dimmer 4CH PWM constant voltage**
Article no.: 170924




## TENDER TEXT

1-4 channel LED dimmer for constant voltage 24VDC. Maximum total output 144W at 24VDC (max. 6A). Input voltage 12-24VDC. Radio control signal. PWM frequency 400Hz. Protection class IP20. Protection class III. dimensions LxWxH = 72.6x30x18mm BILTON LEDON Technology BL Casambi Dimmer 4CH PWM Article 170924 The controller BL Casambi Dimmer 4CH PWM is operated with Casambi . The controller and has an output voltage of 12-24 . Dimension (L x W x H): 72.6 x 30 x 18

## PACKAGING INFORMATION

| | |
|---|---|
| State of origin | FI |
| Customs tariff number | 8536500500 |
| Net weight [g] | 45.1 |
| Gross weight [g] | 45.9 |
| Gross width [mm] | 100 |
| Gross height [mm] | 19 |

© BILTON LEDON Technology | www.better-light.at
Gewerbepark Harham 2, 5760 Saalfelden | Austria | Phone: +43 6582 71164 | Mail: office@bltechnology.at
Version: 20261119 | Errors and printing errors are reserved.

# BL Casambi Dimmer 4CH PWM

**BL Casambi Dimmer 4CH PWM constant voltage**

Article no.: 170924

| | |
|---|---|
| Gross length [mm] | 140 |
| Net width [mm] | 30 |
| Net height [mm] | 18 |
| Net length [mm] | 75 |

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at