

60BL Drive Basic Compact

BL NM Power supply unit CV 220-240VAC 60W 24VDC 2500mA IP20

Article no.: 170807



Output voltage range



Output power range



Degree of protection (IP)

TENDER TEXT

Constant voltage power supply unit. Input voltage 220-240VAC. Maximum total power 60W (max. 2.5A). Output voltage 24VDC. Protection class IP20. Protection class I. Dimensions LxWxH = 222x53x40mm BILTON LEDON Technology power supply 60BL Drive Basic Compact Article 170807 The power supply can be used up to 60 output power and 24 output voltage. The supply voltage of the power supply is 220 - 240 and has a IP20 protection class and protection class I . Dimension (L x W x H): 222 x 53 mm x 40



60BL Drive Basic Compact

BL NM Power supply unit CV 220-240VAC 60W 24VDC 2500mA IP20

Article no.: 170807



MECHANICAL DATA

Housing	Kunststoffgehäuse
Width [mm]	53
Length	222
Height	40
Model	Static
Control signal	ohne
With overheating protection	yes
Suitable for outdoor use	nein
Degree of protection (IP)	IP20
Core cross section	0,5 - 2,5

ELECTRICAL DATA

Protection class	I
Voltage type	AC
Control signal	ohne
With overheating protection	yes
Input voltage range	220 - 240
Output voltage range	24
Output power range	60
Output current range	2500
Type of dimming	not dimmable
Overload protection	yes
Suitable for constant current	yes
Suitable for constant voltage	yes
Suitable for DC-voltage (primary side)	nein

CONNECTION

Core cross section	0,5 - 2,5
--------------------	-----------

TEMPERATURE TECHNICAL DATA

Ambient/storage temperature	- 40 ... + 70
Ambient temperature during operating	- 20 ... + 45
Lifespan at 20 °C	50000

PACKAGING INFORMATION

State of origin	DE
Customs tariff number	8504408290
Net weight [g]	265
Gross weight [g]	265

60BI-Drive Basic Compact

Gross width [mm] 55

Gross height [mm] 45

Gross length [mm] 225

BL-NM Power supply unit CV 220-240VAC 60W 24VDC 2500mA IP20

Net width [mm] 53

Net height [mm] 40

Net length [mm] 222



SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at

DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at