

Drive REG series installation

BL REG Power supply unit CV 90-264VAC 480W 24VDC 20000mA IP20 Vout adjustable

Article no.: 170506



24

Output voltage range

480

Output power range

IP20

Degree of protection (IP)

TENDER TEXT

REG power supply unit constant voltage. Input voltage 90-264VAC. Maximum total output 480W (max. 20A). Output voltage 24VDC. Protection class IP20. Protection class I. Dimensions LxWxH = 128.5x85.5x125.2mm BILTON LEDON Technology power supply Drive REG series installation Article 170506 The power supply can be used up to 480 output power and 24 output voltage. The supply voltage of the power supply is 85 - 264 and has a IP20 protection class and protection class I. Dimension (L x W x H): 128.5 x 85.5 mm x 125.2



Drive REG series installation

BL REG Power supply unit CV 90-264VAC 480W 24VDC 20000mA IP20 Vout adjustable

Article no.: 170506



MECHANICAL DATA

Housing	Metallgehäuse
Width [mm]	85.5
Length	128.5
Height	125.2
Model	Static
Control signal	ohne
With overheating protection	yes
Suitable for outdoor use	nein
Degree of protection (IP)	IP20
Core cross section	2,5

ELECTRICAL DATA

Protection class	I
Voltage type	AC
Control signal	ohne
With overheating protection	yes
Input voltage range	85 - 264
Output voltage range	24
Output power range	480
Output current range	20000
Type of dimming	not dimmable
Overload protection	yes
Suitable for constant current	nein
Suitable for constant voltage	yes
Suitable for DC-voltage (primary side)	yes

CONNECTION

Core cross section	2,5
--------------------	-----

TEMPERATURE TECHNICAL DATA

Ambient/storage temperature	- 40 ... + 80
Lifespan at 20 °C	30000

PACKAGING INFORMATION

State of origin	CN
Customs tariff number	85043180
Net weight [g]	1500
Gross weight [g]	1500
Net width [mm]	128.5

Net height [mm] 85.5
Net length [mm] 129.2

Drive REG series installation

BL REG Power supply unit CV 90-264VAC 480W 24VDC 20000mA IP20 Vout adjustable

SAFETY INFORMATION: Read the safety and installation instructions carefully and completely before commissioning. The operating instructions can be found at: www.better-light.at



DISCLAIMER OF WARRANTY: The technical information corresponds to the status at the time of printing and have been worked out to the best of our knowledge. However, errors and printing errors are reserved. Make sure that you always use the latest version of the data sheets. The latest data sheet can be found at: www.better-light.at